

Amendments to the Claims

1. (Original) A method for detecting a multipath component of packet data at a receiver, comprising:

identifying viable multipath components received by a receiver during an active period of data transmission, whereby packet data is transmitted; and

searching for a multipath component during an inactive period of said data transmission, including defining a dynamic acquisition search window having a time width which increases in proportion to a time duration of the inactive period.

2. (Currently Amended) The method according to claim 1, wherein the dynamic acquisition search window has an initial start  $W_{0s}$  and an initial end  $W_{0e}$ , a time  $t$  of an inactive period, and a start point as a function of time  $W_s$  and an end point as a function of time  $W_e$ , wherein:

$$W_s = W_{0s} - (5/6)t \text{ when } W_{0s} - (5/6)t > 0$$

and

$$W_s = 0 \text{ when } W_{0s} - (5/6)t \leq 0;$$

and

$$W_e = W_{0e} + (5/6)t \text{ when } W_{0e} + (5/6)t < \text{WIN\_SRCH\_MAX}$$

and

$$W_e = \text{WIN\_SRCH\_MAX} \text{ when } W_{0e} + (5/6)t \geq \text{WIN\_SRCH\_MAX};$$

where WIN\_SRCH\_MAX is an arbitrarily selected upper limit for the maximum search window size.

3. (Original) The method according to claim 2, wherein WIN\_SRCH\_MAX is related to a radius of a cell associated with the receiver.

4. (Original) The method according to claim 1, wherein identifying viable multipath components during ~~an~~ active period of data transmission comprises searching for multipath components of packet data using a standard search window associated with a rake finger in a rake receiver having the greatest power amongst the rake fingers in the rake receiver.

5. (Original) The method according to claim 1, wherein viable multipath components received by ~~a~~ receiver during ~~an~~ active period are identified until no multipath components are received by the receiver.

6. (Original) The method according to claim 1, wherein a transmitter transmitting the packet data is a mobile terminal that moves relative to the receiver during one or both of the active period and the inactive period.

7. (Original) The method according to claim 6, wherein a width of the dynamic acquisition search window is increased in correspondence with an expected maximum speed of the mobile terminal.

8. (Original) The method according to claim 1, wherein the receiver is a mobile terminal that moves relative to a transmitter during one or both of the active period and the inactive period.

9. (Original) The method according to claim 8, wherein a width of the dynamic acquisition search window is increased in correspondence with an expected maximum speed of the mobile terminal.

10. (Original) A method for acquiring a packet data multipath component at a receiver, comprising:

associating a standard search window with a first packet data multipath component received at the receiver;

upon loss of the first packet data multipath component, defining an acquisition search window having an initial width corresponding to the standard search window;

searching for a second packet data multipath component across a width of acquisition search window; and

until a second packet data multipath component is detected, expanding a width of the acquisition search window in proportion to a period of time elapsed since loss of the first packet data multipath component and searching for a second packet data multipath component across a width of the expanded acquisitions search window.

11. (Original) The method according to claim 10, wherein searching for a second packet data multipath component comprises:

comparing a detected signal with a reference signal;

determining a value corresponding to the comparison of the detected signal and the reference signal;

repeatedly shifting the detected signal incrementally relative to the reference signal, comparing the relatively shifted detected signal and reference signal, and determining a value corresponding to the comparison of the detected signal and the reference signal, thereby obtaining a plurality of values corresponding to the comparisons between the detected signal and the reference signal, the incremental shifting continuing up to an instantaneous width of the acquisition search window;

identifying the highest value among the plurality of values corresponding to the comparisons between the detected signal and the reference signal; and

comparing the highest value to a threshold value, such that exceeding the threshold value corresponds with identification of the second packet data multipath component.

12. (Currently Amended) The method according to claim 1, wherein the dynamic acquisition search window has an initial start  $W_{0s}$  and an initial end  $W_{0e}$ , a time  $t$  of an inactive period and  $k$  is a constant corresponding with a maximum rate of change of roundtrip propagation delay, and a start point as a function of time  $W_s$  and an end point as a function of time  $W_e$ , wherein:

$$W_s = W_{0s} - kt \text{ when } W_{0s} - kt > 0$$

and

$$W_s = 0 \text{ when } W_{0s} - kt \leq 0;$$

and

$$W_e = W_{0e} + kt \text{ when } W_{0e} + kt < \text{WIN\_SRCH\_MAX}$$

and

$$W_e = \text{WIN\_SRCH\_MAX} \text{ when } W_{0e} + kt \Rightarrow \text{WIN\_SRCH\_MAX};$$

where WIN\_SRCH\_MAX is an arbitrarily selected upper limit for the maximum search window size\_ and ~~k is a constant corresponding with a maximum rate of change of roundtrip propagation delay.~~

13. (Original) A method for detecting a multipath component at a receiver, comprising:

upon loss of a multipath component, <sup>single step</sup> searching for a new multipath component over a dynamic acquisition search window having a time width which increases in proportion to a length of time during which no multipath component is detected.

AI  
cont

14. (Currently Amended) The method according to claim 13, wherein the dynamic acquisition search window has an initial start  $W_{0s}$  and an initial end  $W_{0e}$ , a time t of an inactive period and k is a constant corresponding with a maximum rate of change of roundtrip propagation delay, and a start point as a function of time  $W_s$  and an end point as a function of time  $W_e$ , wherein:

both  
received  
in claim  
13

$$W_s = W_{0s} - kt \text{ when } W_{0s} - kt > 0$$

and

$$W_s = 0 \text{ when } W_{0s} - kt \leq 0;$$

and

$$W_e = W_{0e} + kt \text{ when } W_{0e} + kt < \text{WIN\_SRCH\_MAX}$$

and

$$W_e = \text{WIN\_SRCH\_MAX} \text{ when } W_{0e} + kt \Rightarrow \text{WIN\_SRCH\_MAX};$$

where WIN\_SRCH\_MAX is an arbitrarily selected upper limit for the maximum search window size and  $k$  is a constant corresponding with a maximum rate of change of roundtrip propagation delay.

15. (Original) The method according to claim 13, wherein searching for the new multipath component comprises:

comparing a detected signal with a reference signal;

determining a value corresponding to the comparison of the detected signal and the reference signal;

repeatedly shifting the detected signal incrementally relative to the reference signal, comparing the relatively shifted detected signal and reference signal, and determining a value corresponding to the comparison of the detected signal and the reference signal, thereby obtaining a plurality of values corresponding to the comparisons between the detected signal and the reference signal, the incremental shifting continuing up to an instantaneous width of the acquisition search window;

identifying the highest value among the plurality of values corresponding to the comparisons between the detected signal and the reference signal; and

comparing the highest value to a threshold value, such that exceeding the threshold value corresponds with identification of the new multipath component.

16. (Original) The method according to claim 1, wherein the dynamic acquisition search window has an initial start point and an initial end point, and a dynamic start point that varies as a function of time and a dynamic end point that varies as a function of time.